

Updating DVR (0-876-01 or 0-876-04) for the PSS Firmware and Config

1. Now you will need to Check the DVR to make sure it is a X1N_AI from the system menu.
2. Download the Firmware and config files from the following link
<https://support.durite.co.uk/helpdesk/KB/View/66092464->
3. Unzip the Update file and copy completely onto a 32GB SD card
4. You should now have a file on the SD card named update which will have the Update file HY_X1N_AI_M0010_B3.5.6_R23051708
5. Download the config file from our help desk and copy directly onto the SD card also.
6. Now you will connect the easy check module to the DVR with the SD Card inserted.
7. Power on the DVR then connect to a Phone/Tablet with the Veyes app installed.
8. Now make the Wi-Fi Connection between the Device and the DVR
9. Now open the Veyes app. Username will be admin and password will be eagle. Then press Login.
10. Once on the main screen select version info from the left menu.
11. Now in the Firmware version Press the arrow button under the upgrade tab.
12. This will load the New Firmware into the DVR.
13. The DVR will update and the restart. You will need to reconnect the Wi-Fi then login again.
14. Once you are logged back into the DVR with the Veyes app.
15. Select other on the left side menu.
16. Now select Import Configuration File.
17. Once this has been done you can disconnect the easy check module and restart the DVR.